

**Laser
Coding &
Marking**



Epoxy coated to prevent corrosion

FEATURES

- Full colour touch screen display
- Highest grade HEPA and carbon technology
- Automatic electronic flow control - maintains a constant extraction rate even as the filter blocks
- Gas and particle sensors to warn the operator
- Operate worldwide with no loss of performance

SPECIFICATIONS

Voltage	90v - 254v
Part Number	1704122
Wattage	1.1kW
Frequency	50Hz / 60Hz
Cabinet Height	1195mm
Cabinet Width	528mm
Cabinet Depth	465mm
Cabinet Weight	70Kg
Sound Level	<60dBa
Airflow	400m3/h

INCLUDED AS STANDARD...

FILTERS



**Main Filter
Code
113498C**

**Description
HEPA/Chemical**



**Pre-filter
Code
111097**

**Description
F8/F9 Labyrinth**



**Pre-filter
Code
200037**

**Description
Chemical
Absorbant Pad**

Find out more:

 www.purex.co.uk

 purex@purex.co.uk

 **+44 (0)1405 746030**

CONNECTION KIT

*Connection kit is included
see overleaf for options*

OPTIONS

Pre-filter

Code:
111057

Description:
F6 Labyrinth

Connection Kits

Hose End
Diameter

Hose
Length

Purex Inlet
Diameter

Code: 100043C


50mm

6m

80mm

Epoxy coated
to prevent
corrosion

Connect
to 50mm
diameter
pipe/port
or Purex
valve



6.0m


Code: 120299

80mm

3m

80mm


Connect
to 80mm
diameter
pipe/port



3.0m

If you do not see a connection kit that fits your machine or pipework, please contact Purex or your representative

Interfacing



Interfacing can remotely start the Purex machine when the connected machine starts.

Interfacing can also warn the connected machine when the Purex machine is in alarm.

Take a look through our Interfacing Guide to see our extensive range of options



Purex International Limited
QWP House, Island Drive
Capitol Park, Thorne
Doncaster, UK
DN8 5UE